



How to Calculate Your DP&L Bill Non-Residential (Rate 187, 167)

You will need:

To **verify you are on Rate 187 or Rate 167** - find the section near the middle of your DP&L bill labeled "Usage Detail", below which the column titled "Rate" should read 187 or 167.

Your monthly kWh Usage is to the left of your Rate number on your DP&L bill. See example below.

Usage Detail											
Meter Number	Meter Use	Billing Period		Billing Days	Meter Reading			Multiplier	Usage	Rate	Rate Description:
		From	To		Previous	Current					
10071976	Actual	06/18/17	07/18/17	30	500	1803	1	167,917	187	Primary	
								391.6			
								320.7			
Current Kw Demand Set on Oct 11 at 11:00AM											
Current KVAR Demand											
Power factor 77.37%											

To verify that your bill is within a 25 to 35 day billing cycle (also on your DP&L bill) - under "Usage Detail" find the column titled "Billing Days". NOTE: this rate worksheet will not correctly calculate bills outside of the 25 to 35 day billing cycle. Net Metering customers see second tab for rates.

For Rate 187 or Rate 167, you will need to find the total electric usage for the month and the billing demand. For customers on Rate 167, you will need to adjust your kWh plus 1%.

Input usage below

kWh Usage:	200,000
kW (Demand):	500.0
Kvar:	242.2

Total Bill	\$ 13,465.85
-------------------	---------------------

Price - To - Compare	\$ 0.045
-----------------------------	-----------------

DP&L Delivery Charges:		
Customer Charge (D20):		\$ 242.12
	A flat fee per billing period of	\$ 242.12
Other Delivery Charges:		
Regulatory Compliance Rider (D31):		\$0.00
	A flat fee per billing period of	\$ -
Demand Charge (D20):		\$ 1,185.42
	Multiply the Billed Demand by	\$ 2.0325100
	Multiply the Billed kVAR by	\$ 0.6984153
Universal Service Rider (D28):		\$ 391.70
	Multiply the Billed kWh 0-833,000 by	\$0.0019585
	Multiply the Billed kWh > 833,000 by	\$ 0.0005700
Energy Efficiency Rider (D38):		\$ 266.82
	Multiply the Billed kWh by	\$ 0.0013341
Uncollectible Rider (D27):		\$ -
	Multiply the Billed kWh by	\$ -
Legacy Generation Rider (D40)		\$ 185.00
	Multiply the Billed kWh 0-833,000 by	\$ 0.0009250
Economic Development Rider (D39):		\$ 16.92
	Multiply the Billed kWh by	\$ 0.0000846
Excise Tax (D33):		\$ 735.32
	0 – 2,000 kWh multiply by	\$ 0.0046500
	2,001 – 15,000 kWh multiply by	\$ 0.0041900
	over 15,000 kWh multiply by	\$ 0.0036300



Distribution Investment Rider (D36):			\$0.00
% of Base Distribution		0.000000%	
Decoupling Rider (D32)			\$0.00
% of Base Distribution		0.000000%	
Rate Stabilization Charge (G12)			\$ 979.06
Multiply the Billed Demand by	\$	1.0021200	
Multiply the Billed kWh by	\$	0.0023900	
Storm Cost Recovery Rider (D30):			\$ 3.48
A flat fee per billing period of	\$	3.4800000	
Transmission Cost Recovery Rider - Non-bypassable (T8):			\$ 520.34
Multiply the Billed Demand by	\$	0.8855978	
Multiply the Billed kWh by	\$	0.0003877	
Multiply the Billed kVAR by	\$	-	
Tax Credit Savings Rider (D41):			\$ (38.09)
% of Base Distribution		-2.66790%	
Other Delivery Charges Total:			\$4,245.97
Total Distribution Charges			\$4,488.09

Supply Charges:			
Standard Offer Rate (G10):			\$ 8,977.76
Multiply the Billed kWh by	\$	0.0448888	
Supply Total:			\$ 8,977.76
Total Bill:			\$ 13,465.85

How charges appear on DP&L's bill			
DP&L Delivery Charges:			
Customer Charge	\$	242.12	
Other Delivery Charges	\$	4,245.97	
DP&L Delivery Total	\$	4,488.09	
Supply Charges			
Supply Total:	\$	8,977.76	

Worksheet valid for calculating bills starting on July 1, 2020. This billing worksheet does not take into account the maximum billing charges for this rate structure.

