



How to Calculate Your DP&L Bill Non-Residential (Rate 117, 127)

You will need:

To **verify you are on Rate 117 or Rate 127** - find the section near the middle of your DP&L bill labeled "Usage Detail", below which the column titled "Rate" should read 117 or 127.

Your monthly kWh Usage and billing demand is to the left of your Rate number on your DP&L bill. See example below.

Usage Detail										
Service	Meter Use	Billing Period		Billing Days	Meter Reading		Multiplier	Usage	Rate	Rate Description:
		From	To		Previous	Current				
Electric	Actual	06/18/17	07/18/17	31	91439	93242	1	1803	117	Secondary Single Phase
					Your billing demand is				11.9	

To verify that your bill is within a 25 to 35 day billing cycle (also on your DP&L bill) - under "Usage Detail" find the column titled "Billing Days". NOTE: this rate worksheet will not correctly calculate bills outside of the 25 to 35 day billing cycle.

For Rate 117 or Rate 127, you will need to find the total electric usage for the month and the billing demand. For customers on Rate 127, you will need to adjust your kWh less 1%.

Input usage below

kWh Usage:	5,000
kW (Demand):	10.0
Adjusted Demand	5.0

Total Bill **\$ 443.38**

Price - To - Compare **\$ 0.056**

DP&L Delivery Charges:		
Customer Charge (D19):		\$ 16.73
	A flat fee per billing period of	\$ 16.73
Other Delivery Charges:		
Regulatory Compliance Rider (D31):		\$ 1.62
	A flat fee per billing period of	\$ 1.62
Demand Charge (D19):		\$ 36.57
	Multiply the kW Demand by	\$ 3.6569905
Uncollectible Rider(D27):		\$ -
	Multiply all Billed kWh by	\$ -
Universal Service Rider (D28):		\$ 5.43
	Multiply all Billed kWh by	\$ 0.0010858
Energy Efficiency Rider (D38):		\$ 19.48
	Multiply the Billed kWh by	\$ 0.0038952
Reconciliation Rider (D40):		\$ 3.29
	Multiply the Billed kWh by	\$ 0.0006587



Economic Development Rider (D39):		\$	1.86
	Multiply the Billed kWh by	\$	0.0003719
Excise Tax (D33):		\$	21.87
	0 – 2,000 kWh multiply by	\$	0.0046500
	2,001 – 15,000 kWh multiply by	\$	0.0041900
	over 15,000 kWh multiply by	\$	0.0036300
Distribution Investment Rider (D36):			\$4.83
	% of Base Distribution		9.06070%
Decoupling Rider (D32):			\$2.59
	% of Base Distribution		4.85000%
Distribution Modernization Rider (D37):		\$	37.94
	Multiply the Adjusted Demand by	\$	0.3812556
	0 – 1,500 kWh multiply by	\$	0.0084618
	1,501 – 125,000 kWh multiply by	\$	0.0066692
	All kWh over 125,000 multiply by	\$	0.0064580
Storm Cost Recovery Rider (D30):		\$	0.81
	A flat fee per billing period of	\$	0.8100000
Transmission Cost Recovery Rider - Non-bypassable (T8):		\$	8.84
	Multiply the Adjusted Demand by	\$	0.5874276
	0 – 1,500 kWh multiply by	\$	0.0027170
	All kWh over 1,500 multiply by	\$	0.0005207
Other Delivery Charges Total:		\$	145.13
DP&L Delivery Total:		\$	161.86

Supply Charges:			
Standard Offer Rate (G10):		\$	281.52
	Multiply the Adjusted Demand by	\$	-
	0 – 1,500 kWh multiply by	\$	0.0664185
	1,501 – 125,000 kWh multiply by	\$	0.0519681
	All kWh over 125,000 multiply by	\$	0.0503366
Supply Total:		\$	281.52
Total Bill:		\$	443.38

How charges appear on DP&L's bill			
DP&L Delivery Charges:			
	Customer Charge	\$	16.73
	Other Delivery Charges	\$	145.13
	DP&L Delivery Total:	\$	161.86
Supply Charges:			
	Supply Total:	\$	281.52